




AM-MUTE3

INSTALLATION AND OPERATION MANUAL



AUSTRALIA AND NEW ZEALAND

www.australianmonitor.com.au

SYDNEY

(NSW & ACT SALES)

149 Beaconsfield Street Silverwater NSW 2128
Private Bag 149 Silverwater NSW 1811
Phone: (02) 9647 1411
Fax: (02) 9648 3698
Email: nsw@audiotelx.com.au

MELBOURNE

(VIC & TAS SALES)

22/277 Middleborough Road Box Hill VIC 3128
PO Box 151 Blackburn South VIC 3130
Phone: (03) 9890 7477
Fax: (03) 9890 7977
Email: vic@audiotelx.com.au

BRISBANE

(QLD SALES)

42 Commercial Road Fortitude Valley QLD 4006
PO Box 871 Fortitude Valley QLD 4006
Phone: (07) 3852 1312
Fax: (07) 3252 1237
Email: qld@audiotelx.com.au

ADELAIDE

(SA & NT SALES)

31 Walsh Street Thebarton SA 5031
PO Box 157 Hindmarsh SA 5007
Phone: (08) 8352 4444
Fax: (08) 8352 4488
Email: sa@audiotelx.com.au

PERTH

(WA SALES)

299 Fitzgerald Street West Perth WA 6005
PO Box 404 North Perth WA 6906
Phone: (08) 9228 4222
Fax: (08) 9228 4233
Email: wa@audiotelx.com.au

AUCKLAND

(NZ SALES)

Unit B, 11 Piermark Drive Albany 1331 New Zealand
PO Box 512 Albany 1331
Phone: (09) 415 9426
Fax: (09) 415 9864
Email: sales@audiotelx.co.nz

EUROPE / ASIA / MIDDLE EAST

www.australianmonitor.com.au

INTERNATIONAL SALES

149 Beaconsfield Street Silverwater NSW 2128 Australian
Private Bag 149 Silverwater NSW 1811
Phone: (02) 9647 1411
Fax: (02) 9648 3698
Email: international@audiotelx.com.au

USA / SOUTH AMERICA

www.australianmonitor.com

SENNHEISER ELECTRONIC CORPORATION

1 Enterprise Drive Old Lyme CT 06371 USA
Phone: 1 860 434 9190
Fax: 1 860 434 1759
Email: jalexander@sennheiserusa.com

INTRODUCTION


The AM-MUTE3 is a highly featured muting module. It offers 3 stage muting for the MX series mixers with input 1 having overall priority, input 2 with priority over all inputs but 1 & input 3 with priority over all inputs but 1 & 2. The AM-MUTE3 also allows for the threshold of the trigger signal to be adjusted along with the release time of the ducked signal. Thankyou for purchasing the Australian Monitor Installation Series AM-MUTE3.



The installation of the AM-MUTE3 involves access to the inside of the mixer or amplifier. Installation should only be attempted by a qualified technician. Always turn off AC power and remove the AC power cord before attempting to access the inside of any Australian Monitor Installation Series mixer or amplifier.

INSTALLATION

Installation into compatible Australian Monitor Installation Series mixers or amplifiers is simple. Please follow these easy illustrations for installation.



OPERATION

This module can be setup to accommodate many different priority requirements

1. THRESHOLD

These three pots control the level at which the muting of the signal occurs. Turning the trimpot counter-clockwise sets the threshold higher so that a louder signal is required before muting occurs. The three pots are for each priority input. Note that when the module is set to have channel 1 and 2 at equal levels of priority, the thresholds for each channel are still set individually.

2. RELEASE/HOLD TIME

There are two controls used in combination to set the release time.

a. Course setting


This DIP switch sets the maximum time that can be set by the trimpot. This can be set to SH (short) or LNG (long).

b. Fine control

This trimpot controls the release time from 1 sec to 5 secs when the DIP switch is set to short or 1 to 25 secs when the DIP switch is set to long.

3. MODE

There are 3 modes of operation and a disable setting. These are set using DIP switches 1 & 2.



S1	S2	MODE
0	0	No priority
0	1	Channel 1 has priority over all channels
1	0	Channel 1 has the highest priority, channel 2 has next priority then channel 3
1	1	Channel 1 and 2 have the highest priority then channel 3