

Pioneer Dj

DDJ-FLX10

4-CHANNEL PERFORMANCE DJ CONTROLLER
FOR MULTIPLE APPLICATIONS

- Track Separation
- Expanded On Jog Display
- Mix Point Link
- DMX output for rekordbox Lighting
- Evolved MAGVEL FADER
- rekordbox and Serato DJ Pro compatibility
- Multicolored jog ring
- Iconic, intuitive design
- USB Type-C terminal

rekordbox

serato DJ Pro

SPLIT. MIX. CREATE.



SPLIT MIX CREATE

4-CHANNEL PERFORMANCE DJ CONTROLLER FOR MULTIPLE APPLICATIONS





SPECIFICATIONS

Software	rekordbox
Frequency response	Serato DJ Pro 20 Hz ~ 20 kHz
S/N ratio	110 dB (USB) 94 dB (LINE) 83 dB (PHONO) 81 dB (MIC)
Total harmonic distortion	0.002% dB (USB) 0.007% (LINE) 0.025% (PHONO)
Input/Output terminals	Inputs
	LINE × 2 (RCA × 2) LINE / PHONO × 2 (RCA × 2) MIC × 2 (XLR & 1/4" TRS jack × 1, 1/4" TRS jack × 1)
	Outputs
	MASTER × 2 (XLR × 1, RCA × 1) BOOTH × 1 (1/4" TRS jack × 1) PHONES × 2 (1/4" stereo jack × 1, 3.5 mm stereo mini jack × 1)
	USB
	USB Type-C × 2
	Others
	DMX OUT (3P XLR) × 1
Power supply	AC adapter (DC 12 V)
Power consumption	1800 mA
Maximum dimensions (W × D × H)	716 × 400.3 × 73.4 mm / 28.2" × 15.8" × 2.9"
Weight	6.7 kg / 14.8 lb
Accessories	Power cord AC adapter USB Type-C cable Serato voucher (Pitch 'n Time DJ) Quick Start Guide Precautions for use Warranty (selected regions only)

PRODUCT FEATURES

TRACK SEPARATION

Load tracks from your music library to the DDJ-FLX10 as normal, then manipulate one, or any combination, of the vocals, drums, and inst (other instruments) to create live remixes and mash-ups. You can even choose specific track parts to apply effects to.



DMX OUTPUT FOR REKORDBOX LIGHTING

Connect DMX-compatible lighting equipment directly to the controller and use rekordbox to create custom lighting effects, or set the software to automatically adapt the color and movement of the lights to progress with the music. There's no need for an external DMX interface.

EXPANDED ON JOG DISPLAY

Customize the information you see on the jogs so there's no need to take your eyes off the decks. Choose from 4 modes, some of which show 3Band Waveforms (rekordbox only), and keep an eye on Mix Point Link and rekordbox vocal position analysis information, as well as Performance Pad status.




EVOLVED MAGVEL FADER

Improved from the 2-sensor system on the DDJ-1000, the MAGVEL FADER on the DDJ-FLX10 uses a 4-sensor system. This allows you to make the tiniest volume adjustments, no matter how small the movement of the crossfader, enabling more musical performances.

MIX POINT LINK

Create slick musical progression in your sets by linking mix points in tracks so the next song kicks in automatically at the perfect moment.



REKORDBOX AND SERATO DJ PRO COMPATIBILITY

The DDJ-FLX10 offers free plug-and-play compatibility with rekordbox and Serato DJ Pro, giving you hands-on control of your favorite software application. DVS support is available for rekordbox via selected subscription plans, and for Serato via a paid license/subscription to Serato DJ Expansions or Serato DJ Suite.



Visit the official rekordbox website for the software's specifications: rekordbox.com



Visit the official Serato website for the specifications of **Serato DJ Pro**

* Disclaimer: Specifications and price are subject to change. | * Pioneer DJ is a trademark of PIONEER CORPORATION and is used under license. | * rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation.
* Serato DJ Pro is a registered trademark of Serato Limited. | * Mac and macOS are registered trademarks of Apple Inc., registered in the U.S. and other countries and regions.
* Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.