

M-800RCT

Designed for exclusive use with the M-8080D, the M-800RCT Remote Audio Control Panel with touch display, can do volume adjustments, routing choices, preset choices and give system information.



Article number:M-800RCT-EB

Specifications

Power source	24 V DC (Powered by M-8080D or M-804EX or external)
Indicator	Touch LC-Display Displays device information: ID, Volume, communication status
Inputs	RD In: Transmits and receives AES3 digital audio plus control data Connect to M-8080D, M-804EX or M-800RC, M-800RCT for daisy chain, RJ45 connector
Outputs	RD EXP: Transmits and receives control data Connect to M-800RC or M-800RCT, RJ45 connector
Controls	Volume / Routing / Presets
Dimensions (W x H x D)	150 x 115 x 28 mm
Dimensions (ø x D)	x 28 mm
Finish	Polycarbonate, ABS resin, traffic white (RAL 9016 or equivalent), Panel.
Operating humidity	90% RH or less (no condensation)
Operating temperature	0°C to +40°C



M-8080D Series

M-800RCT

Appearance