

PC-1860 / PC-1860F PC-1860S / PC-2360

Ceiling Speaker



Vast capacity and flexibility for system expansion beyond conventional system coverage.

PC-1860 / PC-1860F PC-1860S / PC-2360

Ceiling Speaker

The ceiling speakers of the PC-series are suitable for announcements and BGM system use in high quality. The speaker's modern, flat design with small frame harmonizes with modern architecture and decor.

The PC-1860F speaker is equipped with a fire dome to protect and prevents fire from spreading through the ceiling.

Common Features

- > 6W rated input
- > Snap in cable terminal
- > Flat front panel
- > Quick and easy installation


PC-1860F / PC-1860S


- > 12 cm speaker
- Mounting brackets (PC-1860S)
- > Fire dome made of steel (PC-1860F)

PC-1860 / PC-2360


- Easy installation with spring catches
- > 12/16 cm speaker
- > Dust cover

PC-1860F #156 (6.14") Fire dome bracket Fire dome Wing nut Mounting Diagram Mounting Diagram





PC-1860



PC-2360

Specifications

	PC-1860F	PC-1860S	PC-1860	PC-2360
Rated Input	6W (100V), 3W (70V)			
Tappings	6/3/1.5/0.8W (100V), 3/1.5/0.8/0.4W (70V)			
Sensitivity (1 W, 1 m)	95 dB	94 dB		
Frequency Response	170Hz - 20kHz	80 Hz - 20 kHz		60 Hz - 20 kHz
Mounting Hole Diameter	156 mm ±3 mm	150 mm ±3 mm (mounting bracket)	150 mm ±3 mm	200 mm ±3 mm
Speaker Component	5" cone-type			6" cone-type
Connection	Snap in terminal			
Colour	Traffic white (RAL 9016 or equivalent colour)			
Dimensions (ø x D)	180 x 105 mm	180 x 95,6mm	180 × 70 mm	230 × 76mm
Weight	1.0 kg	0.75 kg	0.56 kg	0.74 kg

TOA Electronics Europe GmbH

www.toa.eu